
MICRO COMPUTER SYSTEM





INTRODUCTION

APF welcomes you to the wonderful work of Computer Fun This unit will bring you many hours of entertainment in your own home. Installation is simple, and the MP1000 can be played on any size black and whise TV, or in color on a color felterson. With purchases of additional cartridges from the APF library your choice of games and uses will be unlimited.



UNPACKING GAME

When you remove your APF Microcomputer system from the box you should have,
APF Microcomputer System Console with 2 controllers attached
A.C. Power Supply Model 177800
TYP/Consoler System Consoler System Consolers attached
A.C. Power Supply Model 177800
TYP/Consoler System Section 177800
TYP/Consoler System 177800

SPECIFICATIONS

 APF's Microcomputer Console installs in minutes to the antenna input of any size TV-black and white or color
 1 to 4 players depending on the cartridge you are using

Switch Box allows you to play games or switch to regular TV
 Built in Rocket Patrol Game
 Designed to be played by people of all ages, and skills

Designed to be played by péople of all ages, and skills
 Sound through TV, easily adjusted by volume control on TV
 Size L7"xH41½ "xW111½ "
 Weinbt 336 lbs.

A.C. power supply included

CONTROLLERS

The two controllers are permanently wired to the console. They can be extended from the console and held in the pain of your hand. Each controller has a 4 position Joyatick and a 12 key keyboard. The Joyatick allows movement in the vertical and noncrontal directions. The keyboard contains 10 number keys 0.9 for easy entry, a clear key for changing an entry, and an enter key for completing all entries. In addition, a fire button is located at the rear of the controller. This perses the same function as the center.



MICROCOMPUTER CONSOLE

This unit has been designed for easy use by you. It contains an onloff power awitch and e reset button. It also contains a slot to plug in optional cartridges.

CARE OF UNIT:

*Turn your unit off when not in use

For best care, and long use, the following points should be noted; •Never use any other A.C. Power Supply other than the one specifically designed for your unit, model T-7800. •As with all fine equipment, protect your APF unit from shock, dirt.

dampness, and abrasion. Never clean the unit with solvents such as paint thinner, use only a water dampened soft cloth. Never attempt to take any part of your unit apart, this should be

Adone only by qualified APF Service personnel:

Always turn the POWER switch on the console unit OFF before inserting or removing any cartridges.

Don't try to force the carfridge into the Console Slot.
 Your carfridges are protected from normal wear and tear as they ere fully enclosed. However, care should be taken not to spill liquids on them.

Do not pour liquids into the Cartridge Stot of the Console.
 Do not expose the Console, Controllers, or Cartridges to excessive or extreme heat.
 Do not pick up the console unit by using the controller cables.

NOTE: Your APF game is engineered to prevent phosphor memory of the images on your talavision, if your game is left on for 7 minutes, and is not being used, the unit will eutomatically blank the

uses, and is not being used, in each will automaticely been the acreen. To confinue play, you should preas read, and begin pley again. We also suggest to further protect your TV: When playing the game, turn the contrast of your television set down. Turn your wild for when not it use.

INSTALLATION

A. Channel selection your APF unit has been factory preset to VHI Channel 3. It may be necessary to fine tune your T.V. to obtain a clear picture. If your TV has eutomatic fine tuning control, turn it off.

6. Switch Box

- The switch box allows you to watch either regular TV programs, or to use the MP1000. To attach the switch box: 1. Make sure both the television, and the control unit's power le
- turned oft.

 2. Using a screwdriver, remove the wires going to the VHF input on your TV set. Connect these two wires to the antenna input on the switch box.
- Connect the twin lead wires that are permanently attached to the switch box of the VHF inputs of your TV.
 Plus in the name cable (44 foot wire coming out of the control
- Plug in the game cable, (14 foot wire coming out of the control unit) into the game input of the switch box.
 Finally peel off the adhesive protector from the ewitch box, and
 - Finally peel oft the adhesive protector from the ewitch box, and attach permanently to the rear of your TV. NOTE: You may remove the game wire anytime by just unplugologic it from the switch how.



If the rear of you TV looks like this:
To hook up game do the following:
1. Disconnect fiat wire from TV and connect to:

terminals ewitch box.

2. Connect tiat wire from the switch box "TV" ecrews to VHF terminals on TV and the switch box "TV" expenses to VHF terminals on TV and the switch box "TV" expenses to VHF terminals on TV and the switch box "TV" expenses to VHF terminals on TV and the switch box "TV" expenses to VHF terminals on TV and the switch box "TV" expenses to VHF terminals on TV and the switch box "TV" expenses to VHF terminals are swi

minals on TV eet.



If the rear of your TV looks like this: To hook up game do the following: 1. Move slider to make connection between scraws

- Disconnect cable from TV and plug into switch box at "75 OHM" connector.
 Connect flat wire from TV switch box "TV" screws to terminals.
 - Connect flat wire from TV switch box "TV" screws to on your TV set.



To hook up game do the following:

Disconnect cable from TV and plug into switch box at "75 OHM" connector.
 Connect TV's short loose-hanging cable to connector next to it.

on TV set.

3. Connect flat wire from TV switch box "TV" screws to VHF terminals on your TV set.

FEDERAL COMMUNICATIONS COMMISSION REGULATIONS REQUIRE THE FOLLOWING:

Avoid using any more flat Ywin-Lead from the Switch Box to TV set than Is ausplied with Switch Box. Avoid connecting filst Twin-Lead coming from the Switch Box to any TV antenne or cable TV outlat. Avoid attaching loose wires to your TV antenna terminate when using the MP 1000. Doing any of the above may cause futurizance to nearby TV sets and is against Faderal Communications Commission expulsions.

C. A.C. Power Supply

To use the A.C. Power Supply, turn the control unit power off, plug the Power Supply into the A.C. wall accent 101/120 VAC. In-sert the jack of the A.C. Power Supply into the A.C. socket on the rear right of the Microcomputer Console unit. NOTE: Using an A.C. Power Supply other than the T-7800 can valid out the rear right of the Victorian Valid V

TO START PLAY

- Make all connection as outlined under "installation".
 Turn your TV on, and switch to channel 3.
 Turn off your submatic fine tuning control. (AFT)
- Put the switch box to the game position, Note: To watch regul TV, furn the switch to the TV position.
- Turn the power on by pressing the control ON/OFF Switch (Power)
 It might be necessary to adjust the fine tuning control of your TV to rective a clier and undistorted name perture.
- to receive a clear and undistorted game picture.

 7. Adjust your volume control for the desired volume.

 8. Reset game pushing reset button, When the system is reset the
- heading APF Microcomputer, Game Name, and List of Games will appear.

 9. Select game you want to play by reading the list on screen, and
- entering that game number on either keyboard. 10. The game will now appear, and you may begin playing.

GAME DESCRIPTION

Your APF Microcomputer has an infernel geme celled Rocket Petrol.** This can be played as either a one or two player game. The object of the game is to destroy the most space ships within your allotted one minute period.

One Player

In this mode your opposition is the computer. For the first minute the computer will fire eit the space ables friging to excumulate the most points. For the second minute, you have your chance to beat the computer. Of the an insist you push the fire button, located on the rest of the controller. You have an added advantage of being able to move your firting stollar to to let left or right along the screen. This is accomplished by moving the possible either to the left or right with depending once where you want to locate!

NOTE: Whenever a missile is fired or a rocket is destroyed the volume of the sounds occuring can be adjusted by the volume control on your TV.

The game is timed to ellow each player one minute of firing time. After 30 seconds, the rocket ships increase their soered meking it.

Scoring
The score for the computer will appear on the upper right side of the

Two Players

In this mode, you are competing against another person. Each

more difficult to destroy them.

player is still given his allotted one minute. The player with the higher score is the winner.

INSERTING OPTIONAL CARTRIDGES

To use one of the many cartridges available for your Microcomput you should do the following 1. Turn the MP 1000 off to prolong the life of your cartridge and Microcomputer console. 2. Hold the cartridge so that the name is towards you and reads

right side up.

3. Insert the cartridge carefully into the slot in the center of the console. Be sure the game program is tirmly sexted, but do not try to

torce it. 4. If the cartridge is not properly seated, rull it out, and reviewed it

5. When removing the cartridge, check to see that the power is off. and pull the cartridge straight out of the console 6 Each cartridge will give you playing instructions

TROUBLESHOOTING CHECK LIST

Symptom	Cause and Remedy
No playleld image on TV screen or whitish gray screen.	Switch Box set at "TV" change to "GAME" position Check TV is switched to Check TV is switched to Channel 3 Game cable not properly gaged into the Switch Box Twin-lead wire not properly at Sched to rear poly funit not A.C. Power Supply unit not Check To Switch and to Con- roll will. On/OT Switch not pushed to "ON" possition Adjust TV tine tuning control off.
No Consider TH Discourse	Coutch Box and at 10 AME:

chacos to "TV" Antenna Wire not properly attechnolic 200 OHM accounce Switch Box Twin lead wire not properly attached to rear of TV

Playfield unsharp, unsteady	TV set not fine tuned for best picture. Adjust horizontal control on TV or adjust verti- cal control on TV.
Microcomputer worked before but picture suddenly unsharp, unclear or unstable.	Tune fine tuning control on TV set.
Top and bottom borders of playfield not equal distance from top and bottom edge of TV picture tube.	Adjust vertical height control on TV set
Game playfield does not appear correct	Turn game off and turn on.
Does not play in color on Color TV	Turn off auto tine tune, turn TV color control up, Fine Tune TV

Cause and Remedy

Reminals of TV set or Switch

Turn TV volume up or down

Symptom

No sound from TV

Playfield fuzzy like weak TV station

NOTE: Due to differences in color circuitry on various makes of TV receivers activating the reset button of the MP1000 may not always clear and reset the screan property. If this occurs please but nite MP1000 off for 2-3 seconds, and turn on again. On some receivers it may be necessary to repeat this 2-3 times.

FULL THREE MONTH WARRANTY

APF will repair, adjust and/or replace (at its option) defects in matter all or workmanship, without charge, for a period of three (5) months from the date of first purchase, unless caused by the unreasonable use of this product.

To obtain service under this warranty, return this product to your Dealer with evidence of date of purchase, or return it directly to APF

Service, prepaid, with proof of purchase date. This warranty gives you specific legal rights which vary from state to state.

> 43-17 OUEENS STREET LONG ISLAND CITY NY 11101 or in Canada to

APF SERVICES LTO. 47 VALLEY BROOK OR. DON MILLS, ONTARIO CANADA

ARE ELECTRONICS INCORROBATEO

NEW YORK, N.Y. 10022 PRINTED IN TAIWAN